INSTALLATION INSTRUCTIONS FOR 3955-732 For PENDANT

READ AND SAVE THESE INSTRUCTIONS

WARNING! SHUT POWER OFF AT FUSE OR CIRCUIT BREAKER. AVERTISSEMENT!COUPER LE COURANT AU NIVEAU DES FUSIBLES OU DO DISJONCTEUR

MOUNTING THE FIXTURE (Fig. 1)

- Shut off power at the fuse box or circuit breaker box. If necessary, remove the existing fixture and its mounting hardware.
- Carefully remove the new fixture from the carton and check that all parts are included as shown in the illustration.
- 3. Position the mounting plate (A) on the ceiling and mark the location of the four drywall anchors (L). Pre-drill the holes for the drywall anchors (L). Then insert the drywall anchors (L) into the ceiling.
- 4. Attach the mounting plate (A) to the junction box (not included) using mounting screws (C) (Size: 8-32*1/2"L). The side of the mounting plate marked "GND" must face out.
- Place the wood screws (M) through the holes of the mounting plate (A) and lock into the drywall anchors (L) to secure the mounting plate (A) to the ceiling.

CONNECTION THE WIRES (Fig. 2)

6. Connect the electrical wires as shown in Fig.2, making sure that all wire connectors are secured. If your junction box has a ground wire (green or bare copper), connect the fixture's ground wire to it. Otherwise, connect the fixture's ground wire directly to the mounting plate using the green screw (B) provided.

COMPLETING THE INSTALLATION (Fig. 1)

- Align the canopy (D) onto mounting plate (A) and secure with screws (E).
- Install (3) three candelabra base bulbs up to 60 watts or CFL or LED equivalent (Not included), in accordance with the fixture specification (DO NOT EXCEED THE MAXIMUM WATTAGE RATING!) (NE PAS DEPASSER LA PUISSNCE NOMINALE MAXIMLE!)
- 9. Secure the rod (G) to the all thread (F).
- 10. Secure glass (I) to rod (G) through plastic washer (H1/H2) with finial (J).

Your installation is now complete. Return power to the junction box and test the fixture.

IMPORTANT: FIXTURE SHOULD BE INSTALLED BY A QUALIFIED ELECTRICIAN TO ENSURE PROPER WIRING AND INSTALLATION.



MIN 90°C SUPPLY CONDUCTORS



