

including Patent, Trademark and/or Copyright Laws.



The Minka-Aire® warranty is for one (1) year from the date of purchase from an authorized Minka-Aire® dealer.

This warranty is only valid to the original purchaser or user against all defects in material and workmanship (light bulbs excluded) for one (1) full year. Additionally, Minka-Aire® warrants the motor only for the lifetime of the Minka Aire® ceiling fan (excluding wall controls and electrical components), to the original purchaser or user.

<sup>\*</sup>The warranty is voided with the use of any non-Minka-Aire® electrical devices, E.g., wall controls or electrical dimmer switches, etc.

<sup>\*</sup>The warranty is void once the original purchaser or user ceases to own the fan or the fan is moved from its original point of installation.

<sup>\*</sup>The warranty is void with the use of any hanger bracket (non-Minka Aire or non-fan specific) other than the hanger bracket supplied & installed with this specific fan.

#### **Warranty Service Information**

To obtain warranty service during the warranty period, the purchaser should return the fan with the sales receipt to the original place of purchase. The authorized Minka-Aire® dealer, at its sole discretion, will either repair or replace the fan after verifying the legitimacy of the warranty claim. Replacement is subject to availability of the same model. If the model is unavailable it will be replaced by one of equal value. This is a limited warranty; the original purchaser or user is responsible for the cost of removal and reinstallation of repaired or replacement product.

To obtain the name of the Minka-Aire® authorized dealer nearest you call the Minka-Aire® customer care department at 1-800-307-3267, or contact Minka-Aire® through www.minkagroup.net and select FAQ to answer any questions or if you require additional assistance submit the question form found there.

Date Purchased	Store Purchased	Model Number	F694L	

#### **CONTENTS**

SAFETY RULES1	INSTALLING THE LED LIGHT KIT 7
PACKAGE CONTENTS2	OPERATING THE REMOTE CONTROL/ WALL CONTROL 8
INSTALLING THE MOUNTING BRACKET3	CARE OF YOUR FAN9
ELECTRICAL CONNECTIONS4	TROUBLESHOOTING
FINISHING THE INSTALLATION5	SPECIFICATIONS11
ATTACHING THE FAN BLADE6	







1

# SAFETY RULES

1.Before you begin installing the fan, shut power off the circuit breaker of the fuse box.

- 2.Be cautious! Read all instructions and safety information before installing your new fan. Review accompanying assembly diagrams.
- 3. Make sure that all electrical connections comply with local codes, ordinance, or National Electrical Codes. Hire a qualified electrician or consult a do-it-your self wiring handbook if you are unfamiliar with installing electrical wiring
- 4. Make sure the installation site you choose allows the fan blades to rotate without any obstructions. Allow a minimum clearance of 7 feet from the floor and 18 inches from the top of the blades to the wall.
- 5. If you are mounting the fan to a ceiling fan outlet box, use a U.L Listed metal octagonal outlet box marked'Acceptable For Fan Support'. Secure the box directly to the building structure. The outlet box and its support must be able to support the moving weight of the fan (at least 50 pounds). Do not use a plastic box
- 6. Caution: To reduce the risk of injury use only the screws provided with the outlet box in conjunction with the lock washers provided with the fan.
- 7. If you are mounting the fan to a joist, make sure it is able to support the moving weight of the fan (at least 50 pounds).
- 8. After you install the fan, make sure that all mounting components are secured to prevent the fan from falling.
- 9. Do not insert anything into the fan blades while the fan is operating.
- 10. Turn the fan off and wait for the blades to stop completely before performing any maintenance or cleaning.

SUITABLE FOR USE IN WET LOCATIONS

NOTE: The important safeguards and instructions appearing in this manual are not meant to cover all possible conditions and situations that may occur. It must be understood that common sense, caution and care are factors which can not be built into this product. These factors must be supplied by the person(s) installing, caring for and operating the unit.

NOTE-READ AND SAVE ALL INSTRUCTIONS!

factors must be supplied by the person(s) installing, caring for and operating the unit.

NOTE: READ AND SAVE ALL INSTRUCTIONS!

WARNING

TO REDUCE THE RISK OF FIRE,ELECTRIC SHOCK OR OTHER PERSONAL INJURY, MOUNT FAN ONLY TO A U.L LISTED OUTLET BOX OR SUPPORTING

SYSTEM MARKED ACCEPTABLE FOR FAN SUPPORT AND USE MOUNTING SCREWS PROVIDED WITH THE OUTLET BOX IN CONJUCTION WITH THE

LOCK WASHERS PROVIDED WITH THE FAN. MOST OUTLET BOXS COMMONLY USED FOR THE SUPPORT OF LIGHTING FIXTURES ARE NOT ACCEPTABLE FOR FAN SUPPORT AND NEED TO BE REPLACED. CONSULT A QUALIFIDE ELECTRICIAN IF IN DOUBT.

TO REDUCE THE RISK OF PERSONAL INJURY, DO NOT BEND THE BLADE HOLDERS WHILE INSTALLING BALANCING THE BLADES OR CLEANING THE
FAN. DO NOT INSERT FOREIGN OBJECTS BETWEEN ROTATING FAN BLADES.


TO REDUCE THE RISK OF FIRE OR ELECTRONIC SHOCK, THIS FAN CAN ONLY USE CR793 SOLID-STATE SPEED CONTROL
WITH RC1000 REMOTE CONTROL ONLY.



# PACKAGE CONTENTS

Unpack your fan and check the contents. You should have the following items:

- Mounting bracket
- 2. Fan motor3. Up housing
- 4. LED light kit
- 4. LED light | 5. Blade(3)
- 6. Remote control with holder and 2 mounting screws
- 7. AAA 1.5V battery(2pcs)
- 8. Receiver
- 9. Balancing kit lock washer(7)
- A. Mounting hardware:
  #10x 1.5" Wood screws(4pcs)
  #8x 3/4" Machine screws(2pcs)
  Lock washers(2pcs)
  Washers(4pcs)
  4mm Star washers(2pcs)
  Wire nuts(3pcs)
  Wire nuts(5pcs)
- B. 1/4"x 5/8" Motor Screws with lock washer(7pcs)C. Blade bracket kit x3
  - C. Blade bracket kit x D. Hook



## INSTALLING THE MOUNTING BRACKET


Tools Required: Phillips screw driver; slotted screw driver; step-ladder; wire cutters; electrical tape.


WARNING: All of the parts, hardware and components such as the hanger bracket and hanger ball have been provided for your safety and the proper installation of your new ceiling fan. The use of other parts, hardware or components not supplied by Minka Aire® with the fan will void the Minka Aire® warranty.

REMEMBER To turn off the power. Follow the steps below to hang your fan properly.

Step 1. Secure the Mounting Bracket to the ceiling outlet box using the screws provided with your outlet box in conjunction with the lock-washers provided with the fan. If there is no outlet box, attach the mounting bracket to the ceiling with four screws and washers provided. Make sure the bracket is tight and secured.(FIG.1)

Step 2. Lift fan into position by hanging the motor assembly onto the hook from the ceiling mounting bracket allowing it to hang freely. (FIG.2)






## **ELECTRICAL CONNECTIONS**

**WARNING**: To avoid possible electrical shock be sure electricity is turned off at the main fuse or breaker box before wiring.

WARNING: The use of Dimming devices not compatible with ceiling fans will cause unwanted behavior including loud humming and will cause permanent damage to you fans electrical component.

Note: The Aire Control <sup>®</sup> System is equipped with a learning frequency function which has 1024 code combinations to prevent potential interference from other remote units. The frequency on your Receiver and Transmitter units have been preset at the factory. (Fig. 2 ) No frequency change is necessary, should you desire to install another fan within the same home or area with a seperate frequency code please see the 'frequency interference' troubleshooting section of this instruction manual to learn how to change the frequency.




#### Step 1. Put the Receiver into Motor housing.(FIG.4)


Step 2. Receiver to House Supply Wires Electrical Connections: Connect the WHITE wire (Neutral) from the outlet box to the WHITE wire marked 'AC in N' from the receiver. Connect the BLACK wire (Hot) from the outlet box to the BLACK wire marked 'AC in L' from the receiver. Secure all wire connections with the plastic wire nuts provided. (Fig.5)


Step 3. If your outlet box has a GROUND wire(Green or Bare Copper) connect this wire to the Receiver, Mounting bracket and motor housing Ground wires. If your outlet box does not have a Ground Wire, then connect the Receiver, Mounting bracket and motor housing Ground Wires together. Secure wire connection with the plastic wire connector provided. (Fig. 5)

Step 4 . Motor to receiver wires electrical to connections: connect the RED wire from the receiver to the RED wire from the motor, the YELLOW wire to the YELLOW wire, and the GRAY wire to the GRAY wire. For the light, connect the WHITE wire from the receiver to the WHITE wire from the motor, and the BLUE wire to the BLUE wire. (Fig.6)

After all splices are made, check to make sure there are no loose strands. As an additional precaution we suggest to secure the plastic wire connectors to the wires with electrical tape.









#### FINISHING THE INSTALLATION

- Step1. Loosen another canopy screws and remove from the mounting bracket.(FIG.7)
- Step 2. Loosen the other two canopy screws with star washers by half thread from the mounting bracket. (For L-shape slot on motor housing to be mounting).


  \*Remove the hook before assembling the mounting bracket. (FIG. 7)
- Step3. Lift the motor housing up to the mounting bracket and let the L-shape slot on the motor housing go through the two canopy screws with star washer.(FIG.7)
- Step4. Turn the motor housing until it locks in place at the end section of the L-shape slot, ensure the star washer are between the motor housing and screw head. Secure it by tightenting the two canopy screws and the two canopy screws with star washer. (FIG. 7)
- Step5. Finally attach the up housing to the mounting bracket, and push the up housing onto the canopy screw, turn it until the up housing is locked with "click" sound. Do not over tighten, ensure the up housing keeps an even gap with the motor. (FIG.8)





# ATTACHING THE FAN BLADE

Install the blade and tighten with screws and blade bracket supplied as shown in FIG.9. Notice"THIS SIDE UP"label on fan blades. The blades are not reversible. (FIG.10)




# 7

# INSTALLING THE LED LIGHT KIT

Step 1. While holding the 20W LED assembly under your fan, firmly snap the wire connection plugs togerther. (Fig.11)

Step 2. Attach the 20W LED assembly to the switch box by twisting it tightly. (Fig.11)

Note: To prevent electrical shock, do not disassemble. This is an integrated LED light kit assembly.



## OPERATION THE REMOTE CONTROL/WALL CONTROL

Remote Control only: Install the two 'AAA' 1.5 volt batteries(included). To prevent damage to transmitter remove the battery if not used for long periods of time.

Your DC brushless motor is equipped with a self B. Reverse button: learning frequency function remote control. Restore power to ceiling fan and test the transmitter as below for proper operation:

A. 1. 2. 3. 4. 5 and 6 button:

These six buttons are used to set the fan speed as follows:

1'= minimum speed 2 = low speed

3 = medium low speed 4 = medium speed

5 = medium high speed

6 = high speed

This button is used to change the direction of the rotation of the blades: forward for warm weather or reverse for cool weather.

C. button:

This button turns the power Off to the Fan.

D. O Button:

These buttons turn the light ON or OFF and light. The following instructions apply to ceiling fans that feature a DOWN light as the last time it was turned off.

(button) only or ceiling fans that feature an UP light ( button) and a DOWN light ( button) that are controlled independent of each other;

Press and release the button for the desired light to turn the light ON or OFF. Press and hold the button to set the desired light brightness. The light will cycle between bright and dim settings as long as the button is pressed. The light key also control the brightness settings of the has an automatic auto-resume feature that allows the light to remain at the same brightness

Note: The auto learning function will only mandate within 60 seconds when turning the fan's AC power ON.

 Select desired frequency from the back of transmitter. (FIG.12)
 Press the transmitter's "Off" button, and be


2.Press the transmitter's "Off" button, and hold the "Off" button for over 10 seconds. Once the receiver has detected the frequency, the fan will begin to rotate for a short period and then shut off and the down light of your fan if applicable will blink twice. (There is no indication if your fan is not equipped with a light).

Note: The learning frequency function will continue to retain the last set frequency even when the AC power is shut off.

The DC motor has a built in safety feature against obstruction during operation, if the fan motor senses a obstruction for 60 seconds or more it will get locked and will not rotate until the obstruction has been removed and the power has been disconnected for 5 seconds.

removed and the power has been disconnected for 5 seconds.

3. Over 60W protection: When the receiver detects motor power consumption which is greater than 60W, the receiver's power will—stop and operation will be immediately discontinued. if you want to re-start the fan, Please remove obstacles and disconnect the power by turning off the circuit breaker. And turn the power on after 5 seconds.



Speed settings for warm or cold weather depend on factors such as room size, ceiling height and number of fans.


NOTE: to change the direction of the rotation of the blades the fan must be in operation mode.


Warm Weather (forward)

A DOWNWARD airflow creates a cooling effect as shown in FIG.13. This allows you to set your air conditioner on a warmer setting without affecting your comfort.

#### Cool Weather (Reverse)

An UPWARD airflow moves warmer air off the ceiling area as shown in FIG.14. This allows you to set your heating unit on a cooler setting without affecting your comfort.





# CARE OF YOUR FAN

Here are some suggestions to help maintain your fan.

- 1. Because of the fan's natural movement some connections may become loose. Check the support connections, brackets and blade attachments twice a year. Make sure they are secure. (It is not necessary to remove fan from the ceiling).
- 2. Clean your fan periodically to help maintain its new appearance over the year. CAUTION many common household cleaning products contain chemicals that could damage the finish of your fan. Use only a soft lint free cloth and soapy water.
- 3. If your fan is provided with wood veneer blades; you can apply a light coat of furniture polish for additional protection and enhanced beauty.

Cover small scratches with a light application of shoe polish.

- 4. Use a lint free lightly damp cloth or duster to remove dust from the blades.
- 5. There is no need to oil your fan. The motor has permanently lubricated bearings.
- 6. If your fan is provided with glass shades, clean with lukewarm soapy water and a soft cloth or sponge. DO NOT IMMERSE GLASS SHADES IN HOT WATER. DO NOT PUT GLASS SHADES INTO AN AUTOMATIC DISHWASHER.

#### WARNING!

MAKE SURE THE POWER IS OFF AT THE ELECTRICAL PANEL BOX BEFORE YOU ATTEMPT ANY REPAIRS. REFER TO THE SECTION ELECRICAL CONNECTIONS.

#### **SYMPTOM**

Fan will not start

#### SOLUTION

- Check to make sure the wall switch is turned on.
- Check circult fuses or breakers
- Caution! Make sure the power is turned off before performing the following steps.
- Remove canopy and check wire connections.
- Check wall control transmitter connections (if applicable).
- Note:fan must be installed at a maximum distance of 40 feet from the transmitting unit for proper signal transmission between the transmitting unit and the fan's receiving unit.

SYMPTOM

Fan Sounds Noisy

#### **SOLUTION**

- Allow a 24-hour "break in" period. Most noises associated with a new fan will go away during this time. Make sure the screws that attach the fan blade holder to the motor hub is tight.
- Make sure outlet box is secured to building structure, if necessary use the wood screws provided to further secure outlet box to joist.
- Make sure hanger bracket is secure to the outlet box, screws are tight.

# SYMPTOM

Fan Wobble

SOLUTION

• Note: All blade sets are grouped by weight. Because wood and

tight.

blades are matched

plastic blades vary in density, the fan may wobble even though

• Make sure outlet box is secured to building structure, if necessary use the wood screws provide to further outlet box to joist. • Make sure hanger bracket is secure to the outlet box, screws are

• If a Balancing kit is provided follow the instructions included with

the balancing kit to help correct any excessive wobble.

#### SYMPTOM

SOLUTION

Frequency Interference

1. Turn the power off to your ceiling fan.

2. Please use a small size tool to change the frequency settings on the control system.

3. Return power to the unit.

Note: After the AC power is on, do not press any other button on the transmitter before pressing the "Stop" button, doing so will cause

the procedure to fail.

4. Within 60 seconds of turning the Fan's AC power ON, Press the transmitter's "Stop" button and hold the "Stop" button for 10 seconds. 5. Once the receiver has detected the set frequency, the down light of your fan if applicable will blink twice. (There is no indication if your

fan is not equipped with a light).

repeat the process.

6. The receiver has now learn the frequency which has been selected on the transmitter. After completing the steps above, you should be

able to operate the ceiling fan and light. If the fan is not responding to the transmitter, please turn the power off to the receiver, and

# 11

# **SPECIFICATIONS**


These are typical readings. Your actual fan may vary.
They do not include amps and wattage used by the light(s).

For any additional information about your Minka Aire® Ceiling fan, please write to:

• [	Fan Size	Speed	Volts	Amps	Watts	RPM	N.W.	G.W.	C.F.
	52″				1.77 18.54				1.607



#### PERFORMANCE AND ENERGY INFORMATION



For any additional information about your Minka Aire® Ceiling fan, please write to;

FAN SPEED	AIRFLOW (CFM)*	POWER USE (watts)	AIRFLOW EFFICIENCY (CFM/watt)
Low	978	1.77	552.54
High	3983	18.54	214.83

Ceiling fan airflow is measured in cubic feet per minute (CFM). Power use is measured in watts. To maximize energy savings:

- Choose a fan with high airflow efficiency (CFM/watt).
- Use DOE -labeled lighting in your fan.
- Remember to switch off your fan when you leave the room,

\* Measured according to the DOE approved Solid State test method

