INSTALLATION INSTRUCTIONS

Item# P1333-780

READ AND SAVE THESE INSTRUCTIONS

WARNING! SHUT POWER OFF AT FUSE OR CIRCUIT BREAKER. VERTISEMENT! COUPER LE COURANT AU NIVEAU DES FUSIBLES OU DU DISJONCTEUR.

ASSEMBLING THE FIXTURE (Fig. 1)

1. To begin assembly of your fixture, take the cluster assembly (3) and slip frame (2), knurled nut (a) along wire and thread fixture's loop (J) onto threaded tube (1) and tighten. -Crossbar

HANGING THE FIXTURE (Fig. 2)

- 2. Thread all thread (D) into collar loop (F) until snug.
- 3. Thread the other end of all thread (D) into crossbar. Note, the length of all thread (D) into crossbar maybe adjusted if necessary.
- 4. Use lock washer (B) and hex nut (E) to secure all thread (D) to crossbar (A).
- Take crossbar assembly and mount to junction box (JB) with 8-32 mounting screws. The side of crossbar (A) marked with "GND" must be face out.
- 6. Open and connect quick link (G) to fixture loop (J) then slip canopy (H) and collar ring (I) over quick link (G) and allow them to rest at top on fixture's loop (J).
- 7. Feed fixture wires through collar loop (F) and crossbar assembly.

CONNECTING THE WIRE (Fig. 3)

- 8. Connect the electrical wire as shown in Fig. 3, making sure that all the wire connectors are secured. If your junction box has a ground wire (green, or bare copper), connect fixture's ground wire to it. Otherwise connect fixture ground wire directly to crossbar (A) using green screw provided.
- 9. Open guick link (G) and connect to loops (F/J). Then close guick link.
- 10. Tuck wire connections neatly into junction box (JB).
- 11. Raise canopy (H) over ceiling loop (F) and secure with collar ring (I).

FINISHING THE FIXTURE (Fig. 1)

12. Install 4x E12 base light bulbs (LB) up to 60 watts each or CFL or LED equivalent (not included) in accordance with the fixture specification.

DO NOT EXCEED THE MAXIMUM WATTAGE RATING! (NE PAS DEPASSER LA PUISSANCE NOMINALE MAXIMALE!)

Your installation is now complete. You can now turn the power ON and test the fixture.

Note: Illustration (Fig. 1) on this manual is for installation purposes only. It may or may not be identical to the fixture purchased.







